

To access GUI and upgrade the ECB6000 Firmware

- 1) Set a static IP on the Computers Network adapter of "192.168.144.5"
- 2) Open the Web Browser and type "192.168.144.20" and press enter.
- 3) The admin user name is admin and the admin password is ecb6000.
- 4) Click on "Upgrade".
- 5) Click on "Choose File" and select the "[AEI_v3.01_NCS_firmware.bin](#)" file that was provided.
- 6) Click on upload.

The device will upload and upgrade the adapter then reboot. After reboot the SW Version should now show "EN2850.1.54.06.89"

- 7) Make sure to set the Computers Network adapter back to "Obtain Automatically".

Note:

Actiontec does NOT provide support on changing any settings in the adapters as they are already preconfigured with optimal settings.